

Artistic Licence Power Supply Compatibility Chart

Power Supply	Powered Product	Product per PSU	O/P Voltage	O/P Current	Power Watts	Duty Cycle	CE	FCC	PSE	Input Connector	Output Connector	Input Voltage
PSU-9-1.5-DCJ	Micro-Scope 3a	1	9.00	1.50	13.50	80.00%	✓	✓	✓	IEC	DC Jack	Universal
	Show-Control	1										
	Common-Sense	2										
	MIDI-Scope	1										
	Preset-6	1										
	Preset-12	1										
PSU-9-1.5-XLR4	Snap-1024	1										
	Net-Lynx O/P	1	9.00	1.50	13.50	80.00%	✓	✓	✓	IEC	XLR 4	Universal
	Net-Lynx I/P	1										
	DMX-Split RDM	1										
	Power-Hub 4	1										
PSU-9-1.5-FER	DMX-Fix	1										
	Light-Switch	4	9.00	1.50	13.50	80.00%	✓	✓	✓	IEC	Ferrules	Universal
	Dimmer-Switch	4										
	Rail-Split RDM	2										
	Rail-Switch	2										
	Rail-DALI	2										
PSU-9-1.5-DR2	Sign-Control	2										
	Two-Play	1	9.00	1.50	13.50	80.00%	✓	✓	✓	IEC	Ferrules	Universal
	Art-Relay	1										
PSU-9-10-DR	Art-Lynx	2										
	Multichrome-E2	0.5	9.00	10.00	120.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
PSU-12-6-FER	Flexi-Strip Range	x	12.00	6.00	75.00	80.00%	✓	✓	✗	IEC	Ferrules	Universal
PSU-12-6-DR	Flexi-Strip Range	x	12.00	6.00	75.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
PSU-12-10-DR	Flexi-Strip Range	x	12.00	10.00	120.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
PSU-24-2-WM2	Insta-Lynx	0.5	24.00	2.00	48.00	80.00%	✓	✓	✗	IEC	Weidmuller 2 pin	Universal
	Tour-Lynx	0.5										
PSU-24-2-FER	Rail-Demux	1	24.00	2.00	48.00	80.00%	✓	✓	✗	IEC	Ferrules	Universal
	Rail-Switch	2										
	Rail-DALI	2										
	Rail-PSU-D4	1										
PSU-24-5-FER	Rail-Pipe	1	24.00	5.00	120.00	80.00%	✓	✓	✗	IEC	Ferrules	Universal
	Rail-Demux	2										
	Rail-Switch	4										
	Rail-DALI	4										
	Rail-PSU-D4	2										
PSU-24-2.5-DR	Art-Relay	2	24.00	2.50	60.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
	Art-Lynx	2										
	Rail-Demux	1										
	Two-Play	2										
	Sign-Control	2										
	Rail-Switch	2										
	Rail-Split RDM	2										
	Rail-DMX-DALI	2										
	Rail-DALI-DMX	2										
	Rail-DMX-DSI	2										
PSU-24-5-DR	Rail-PSU-D4	2										
	Rail-Pipe	1	24.00	5.00	120.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
	Rail-Pipe HC	0.5										
PSU-24-10-DR	Art-Pipe	0.5										
	Rail-Pipe	2	24.00	10.00	240.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
	Rail-Pipe HC	1										
	Art-Pipe	1										
PSU-48-1-DR	Candle-Power	1										
	Art-Switch PoE4	1	48.00	1.25	60.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
PSU-48-5-DR	Art-Switch PoE4	4	48.00	5.00	120.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
	Art-Lynx	4										
	Art-Relay	4										
	Candle-Power	1	48.00	10.00	240.00	80.00%	✓	✓	✗	DIN Rail PSU, Screw Terminal		Universal
PSU-48-10-DR	Art-Switch PoE4	8										(Switched)

Note: Many products can be powered by several different power supplies. This is particularly useful when designing power distribution for a number of the products in the same installation. The cell coloured light green indicates the best choice of PSU for a single product.